

# Ei414



## RadioLINK+ Fire/CO Alarm Interface



- Connects Aico domestic alarms to external devices, such as Fire Panel systems, Telecare/Warden Call and Sprinkler systems
- Mains powered with Rechargeable Lithium Back-up
- RadioLINK+ Wireless interconnection
- Key Switch to control on, off and test status
- 5 year guarantee



### Description

The Ei414 RadioLINK Fire/CO Alarm Interface connects Aico fire and CO alarms with a range of external devices. The module will receive 'Fire', 'CO' and 'Service' signals from RadioLINK devices and switch the relevant built-in relay

### Technical

<b>RF Frequency (MHz)</b>	868.499	<b>RF Range (m)</b>	>100 in free air
<b>Indicators</b>	Green - Power / Red - CO, Fire or Service / Blue - RF transmission	<b>Supply Voltage (V)</b>	230/10-30
<b>Voltage Type</b>	AC/DC	<b>Battery Type</b>	Lithium rechargeable
<b>Power Consumption (W)</b>	1.6(AC) / 1.8(DC)	<b>Technologies</b>	RadioLINK+

### Dimensions & Weights

<b>Depth (mm)</b>	50	<b>Height (mm)</b>	100
<b>Width (mm)</b>	220	<b>Product weight (kg)</b>	0.393
<b>Packaged weight (kg)</b>	0.444		

### Approvals & Warranty

<b>Certification/Approvals</b>	R&TTE / EMC / LV	<b>Warranty</b>	5 year warranty
<b>EAN Number</b>	5099383005066		

### Environmental

<b>Humidity Range (%)</b>	15-95	<b>Temperature Range (°C)</b>	-10 to 40
---------------------------	-------	-------------------------------	-----------