

TIMEGUARD®

Wi-Fi 3 Way Power Strip with USB Ports

Model: WFTRS3GUSB



Installation & Operating Instructions

1. General Information

These instructions should be read carefully in full before installation, and retained for further reference and maintenance.

2. Safety

- Do not plug in any appliance that exceeds the capacity of the Smart Plug.
- Always ensure the plug of any appliance is fully inserted into the Smart Plug outlet.
- If cleaning of the Smart Plug is required, remove from mains power and wipe Smart Plug with a dry cloth.
- Do not immerse in water or any other liquid.
- For indoor use only.

3. Technical Specifications

- 230V AC 50 Hz
 - Switch Rating: 13A
 - Manual ON/OFF Control
 - USB Port Output: 5V 2.4A / Port
 - Operating Temperature: -30°C to +65°C
 - Operating Humidity: ≤80%RH
 - WLAN-Standard: 802.11 b/g/n
 - Encryption: WEP/WPA/WPA2
 - CE Approved
 - EC Directives: Conforms to the latest directives
- Dimensions (H x W x D): 60 x 248 x 32mm

4. System Requirements

- Smartphone/Tablet with at least iOS 8.0 or Android 5.0
- WLAN-enabled router: 2.4GHz (Separate Band)
- Tuya Smart App

5. Downloading App and Registration

Note: The smartphone or tablet must be connected to a 2.4GHz band on the router. Paring on the 5GHz band will result in paring either timing out or being unsuccessful. Refer to your ISP (Internet Service Provider) on separating the bands if required.

- Ensure your phone or tablet is connected to your local Wi-Fi network.
- Download the Tuya Smart App onto your phone or tablet by searching for 'Tuya Smart' on Google Play Store or the App Store. You can also scan the applicable QR code right;



- Install the App and open it to the registration screen. Click on the '**Register**' button.
- Tap '**Agree**' to accept the privacy policy.
- Choose your region by selecting the Country Code. Enter your email address or phone number and click '**Get Verification Code**'.
- Enter the Verification Code sent to the email address or phone number that you provided. Once you have successfully entered the code, it will automatically move you to the Password screen.
- Assign a Password (this must be between 6 to 20 characters including letters and digits) and click '**Done**'.
- You are now registered and by default will see the App home page.

6. Home Management

Note: Before adding any devices to your account, structuring your household (or the property) may be a consideration if you plan on using Smart devices in different rooms or locations.

- Select the '**Me**' option from the home page which will navigate you to your personal settings. From here you can setup a nickname for your profile i.e. 'Mr Smith's Account. After this select the '**Home Management**' option.

- Select the '**Home Name**' option and enter your last name or even '**My Home**' if preferred. (This is required to allocate devices to separate rooms later once paired).
- Next tick the rooms you wish to assign to your account; this can be changed at any time and custom room names can also be added.
- To navigate back to the home screen, press the '**Back**' button, and then click Home.

7. Pairing your Device(s)

Note: If you are using a VPN, make sure this is disabled before continuing.

- To add a new device to your account, click the '**Add Device**' button (or click on the + button in the top right hand corner)
- Notice the different categories of products; it is essential that the correct product is selected for the pairing process to be successful. For the Wi-Fi 3 Way Power Strip, choose the '**Power Strip (Wi-Fi)**' option from the list.
- Plug the Wi-Fi 3 Way Power Strip into a socket with the power switch in the ON position. Press and hold the square On/Off button for a few seconds until the LED starts to flash.

- When the LED is flashing press the **'Confirm indicator rapidly blinking'** button. Enter the password for the network and press the 'Confirm' button to pair the product to your account (In most cases the password should autofill).
- The App will pair the smart product to the network. The time it takes for pairing to complete, which will differ depending on the network connection. Shortly into the pairing process, the flashing Status LED will become stable (ON). This indicates that the product has joined the network.
- To rename your product, select the pencil icon. If this is not required, click on the **'Done'** button and you will be guided to the device controls menu.
- To navigate back to the home screen, press the **'Back'** button. The newly paired Wi-Fi Smart Switch will now be listed.

Note: If the pairing process was not successful, disconnect the mains supply from the product and re-establish power to the unit. Follow the bullet points from 'Section 7' to try again.

8. Smart Home Assistant

- To add your device to your Smart Home Assistant services, such as Google Home or Amazon Alexa, follow the on-board instructions located on the TuyaSmart App. To do this, select the **'Me'** option from the home menu, and then select **'More Services'**.

- On the more services screen, you will see support or different applications for automated Smart Home control. Follow the instructions on the TuyaSmart App to add the devices to your Smart Home Assistant service.

Note: The Smart Home Assistant services supported by the TuyaSmart App may change as it is a 3rd party App Service. Any services that may be removed are the responsibility of TuyaSmart developers and not Timeguard.

9. Support

Note: If you have any concerns that the intended application of this product does not meet your requirements, please contact Timeguard directly prior to installation.

10. Guarantee & Company Details

3 Year Guarantee

In the unlikely event of this product becoming faulty due to defective material or manufacture, within 3 years of the date of purchase, please return it to your supplier in the first year with proof of purchase and it will be replaced free of charge. For years 2 to 3 or any difficulty in the first year, telephone our helpline.

Note: a proof of purchase is required in all cases. For all eligible replacements (where agreed by Timeguard) the customer is responsible for all shipping/postage charges outside of the UK. All shipping costs are to be paid in advance before a replacement is sent.



If you experience problems, do not
immediately return the unit to the store.
Telephone the Timeguard Customer Helpline:

HELPLINE
020 8450 0515

or email
helpline@timeguard.com

Qualified Customer Support Coordinators
will be online to assist in resolving
your query.



A **theben** Group Company

For a product brochure please contact:

Timeguard Limited.
Victory Park, 400 Edgware Road,
London NW2 6ND
Sales Office: 020 8452 1112
or email csc@timeguard.com
www.timeguard.com